

AMSL6A200 BACKUP DEPTH AND SPEED DISPLAY Operations and Maintenance Manual



TABLE OF CONTENTS

SECTION	DESCRIPTION
1.0	GENERAL DESCRIPTION
2.0	OPERATING PROCEDURES
3.0	DESCRIPTION OF FEATURES
4.0	MENU SELECTIONS
5.0	INSTALLATION PROCEDURES
6.0	SPECIFICATIONS
7.0	PARTS LISTS AND DIAGRAMS

1.0 GENERAL DESCRIPTION

The Backup Depth System is designed to be an independent depth and line speed measurement indicator.

The system consists of two devices, the display panel and the magnetic pickup. The display panel (shown below) is designed to be mounted inside the wireline unit.



The magnetic pickup (shown below) is mounted to the speedometer drive output from the measuring head.



The unit is powered by three internal rechargeable batteries. It can be connected to an external AC or DC power source to keep the batteries charged.

The unit is designed to operate without intervention from the user. When external power fails, the depth display is maintained by the batteries. If the magnetic pickup is inactive for more than one hour, the depth is stored and the unit switches it self off.

Front panel controls allow the operator to:

- Zero the depth reading
- Adjust the depth value
- Select a different settings using the menu button
- Switch the power off manually (for use when running on battery power)

The unit cannot be switched off when connected to external power.

The unit is switched on automatically, when external power is restored, or when the user selects the enable switch on the front panel

The display unit forces you to use two switches. The enable switch must be pressed in conjunction with the zero or depth adjust switch to prevent accidental loss or corruption of the depth display value.

The panel has a built in data recorder that stores depth and line speed data in text format. The panel also has a built in internal clock that runs continuously whether powered up or not. This clock is used to provide a time and date stamp for every data record.

Following is an example of the data showing the format.

```

BenchMark Wireline Products ALS6A200 ver 1.00
  date      time      depth  speed
01/01/00,00:04:07,    0.0,    0.0
01/01/00,00:04:09,    1.8,    95.5
01/01/00,00:04:10,    4.7,   161.6
01/01/00,00:04:11,    6.0,   452.9
01/01/00,00:04:12,    6.1,    51.1
01/01/00,00:04:13,    9.0,   228.2
01/01/00,00:04:14,   12.6,   225.5
01/01/00,00:04:15,   16.5,   220.0
01/01/00,00:04:16,   20.4,   210.4
01/01/00,00:04:17,   23.5,   168.1
01/01/00,00:04:18,   24.1,    77.5
01/01/00,00:04:19,   24.3,    37.0
01/01/00,00:04:20,   24.6,    37.0
01/01/00,00:04:21,   24.8,   12.8
  
```

2.0 DESCRIPTION OF FEATURES

2.1 Enable Switch

The ENABLE/OFF switch is a center-biased three position switch. It is used for several things:

The up position powers the unit on, and the unit displays the stored value.

It must be in the up position to zero or increase/decrease depth.

If the switch is pressed down, the panel stores the displayed value in non-volatile memory and switches the unit off if not connected to external power.

The unit cannot be switched off when connected to external power.

Pressing it down also turns off the data recorder. It is recommended that the data recorder be switched off before removing the memory card.

To turn the data recorder on the switch must be pressed up and the zero button pressed. The data recorder will remain on until it is turned off.

When the panel is first powered up the data recorder is powered on.

2.2 Menu Switch

This button is used to change the internal settings of the panel. These settings include Measuring Head type, Line Size settings, Load Cell Angles, English/Metric units, Depth adjust (auto add/subtract), etc. Refer to section 4 for detailed description of these features.

2.3 Zero Switch

The ZERO switch allows you to zero the display, it is a two position momentary switch. To activate this switch, you must hold the ENABLE switch up, then press this switch up.

The rate of increase (or decrease) is controlled by the length of time the INCREASE/DECREASE switch is held in position. For small adjustments, hold the ENABLE switch up and jog the INCREASE/DECREASE switch.

2.4 Increase / Decrease Switch

The INCREASE/DECREASE switch is a center biased three position switch. Use the ENABLE switch to activate this switch:
Hold both the enable and the increase/decrease switches up and the display value increases
Hold the enable switch up, and the increase/decrease switch down and the display value decreases.

2.5 EXT PWR LED

There is one LED on the front panel of the display unit. The LED is lit when the unit is connected to an external power source, either 240/120 vac or 12 vdc. If the LED is not lit, then the unit is operating off of battery power.

3.0 OPERATING PROCEDURES

- 3.1 Turn the unit on by pressing the enable switch up. If external power is applied, the unit will power on automatically.
- 3.2 Select the appropriate settings from the menu (see section 4.0)
- 3.3 Set the depth to the proper value by using the set depth switches or to 0 by pressing the zero switch. Note: the enable switch needs to be pressed in order to set depth.
- 3.4 The system is now ready to measure depth.
- 3.5 After each run in the hole, reset the zero value before entering the hole again. Note: the enable switch needs to be pressed in order to zero the depth.

Some of the Industry standard wheel sizes in use are:

CIRCUMFERENCE (FT) COUNTER TYPE

3.4034	ASEP – MP13
4.2359	ASEP – MP16
5.4009	ASEP – MP20
2 (MENU)	ASEP SMART HEAD
4 (MENU)	HALLIBURTON TWO WHEEL (UNIVERSAL)
2 (MENU)	OTIS 2’ WHEEL
4 (MENU)	OTIS 4’ WHEEL
.6667	LEE SLICKLINE COUNTER (FEET WHEEL)
.6562	LEE SLICKLINE COUNTER (METRIC WHEEL)
2 (MENU)	LEE BRAIDED LINE COUNTER (FEET WHEEL)
1.6404	LEE BRAIDED LINE COUNTER (METRIC WHEEL)
3.9424	SSR
1	GEOLOG 3’
1	GEOLOG 2’
2.5167	BAKER DWMD

NOTE: MENU indicates that there is a menu selection for this counter. If there is no menu selection, use wheel size OTHER.

4.0 MENU SELECTIONS

The internal settings of the panel can be set by pressing the menu button.

To change a setting, press and release the menu button until the desired setting is displayed. Use the +/- switch to change the setting. After a setting is changed, continue pressing the menu button until you pass the last setting. At this time you will be asked if you want to ACCEPT the setting changes. To accept the changes press + then the MENU button. If you press – or wait for four seconds, the changes will be ignored. If you wait for four seconds between switch presses, the panel will time out and go back to displaying depth.

Following is a summary of the process.

PRESS MENU

CHANGE DISPLAYED PARAMTER BY PRESSING +/- SWITCH

PRESS MENU BUTTON AGAIN

CHANGE DISPLAYED PARAMTER BY PRESSING +/- SWITCH

CONTINUE UNTIL **ACCEpT** IS DISPLAYED.

PRESS + TO SAVE THE SETTINGS

PRESS MENU BUTTON AGAIN WHEN **YES** IS DISPLAYED.

Note: If + is not entered or the menu button is not depressed when YES is displayed, any changes made to the parameters will not be saved.

There are four different menus, one for each of the different type of measuring systems.

- 3 – Kerr AM3K Cased Hole Measuring head
- 5 – Kerr AM5K Open Hole / Cased Hole Measuring head
- SL – Kerr dual 16” Wheel Slickline Measuring head
- OT – Other wheel size

To change the head type, press the menu button until Hd is displayed. At this time press the +/- button until the desired head type is selected. Press + then the menu button again to accept the setting.

Each head type has a different menu. Following are the available settings for each.

4.1 MODE 3

This mode is for a BenchMark AM3K cased hole measuring head.

The available menu selections in AM3K mode are:

LS (LINE SIZE)

This selection is use to choose the size of the cable you will be using. This setting will adjust the wheel size to account for the size of cable.

The available sizes are:

3/8, 5/16, 9/32, 1/4, 7/32

The wheel size settings for each are:

3/16" cable – 2.014 ft.
7/32" cable - 2.017 ft.
1/4" cable – 2.020 ft.
9/32" cable – 2.023 ft.
5/16" cable - 2.026 ft.
3/8" cable – 2.031 ft.

AdJ (DEPTH ADJUST)

This setting is comparable to shimming a wheel. The amount selected will automatically be added or subtracted from the depth input. The values are feet / thousand.

Un (DEPTH UNITS)

This setting is used to set the display readout units to either FEET or METERS.

dir (DIRECTION)

This setting is used to reverse the counting direction. The depth should be increasing as you are going into the hole and decreasing as you are coming out of the hole. If it is going the opposite direction, use this setting to change it.

4.2 MODE 5

No wheel size selections are available. It is set for a 2' circumference measuring wheel. Use the setting for any straight-line measuring device that uses a 2 foot measuring wheel.

Use this mode for the Kerr AM5K measuring head.

The available menu selections in mode 5 are:

AdJ (DEPTH ADJUST)

This setting is comparable to shimming a wheel. The amount selected will automatically be added or subtracted from the depth input. The values are feet / thousand.

Un (DEPTH UNITS)

This setting is used to set the display readout units to either FEET or METERS.

dir (DIRECTION)

This setting is used to reverse the counting direction. The depth should be increasing as you are going into the hole and decreasing as you are coming out of the hole. If it is going the opposite direction, use this setting to change it.

4.3 MODE SL

This mode is to be used for slickline measuring systems. There are several different selections available which make it flexible enough to work with virtually any type of slickline measuring head.

Selections are available for different wheel sizes, line sizes, and groove sizes.

Use this mode for a Kerr SHARK or HammerHead slickline system using a 4' counter wheel.

The available menu selections in SL mode are:

LS (LINE SIZE)

Select the size of the wireline you will be using. This setting will adjust the wheel size to account for this size of cable.

The available sizes are:

.082
.092
.108
.125
3/16
7/32
1/4
OtH (OTHER)

AdJ (DEPTH ADJUST)

This setting is comparable to shimming a wheel. The amount selected will automatically be added or subtracted from the depth input. The values are feet / thousand.

Un (DEPTH UNITS)

This setting is used to set the display readout units to either FEET or METERS.

dir (DIRECTION)

This setting is used to reverse the counting direction. The depth should be increasing as you are going into the hole and decreasing as you are coming out of the hole. If it is going the opposite direction, use this setting to change it.

SEtUP

If you press + when at setup, the following options become available.

C (WHEEL CIRCUMFERNCE)

The following five options are available.

2 ft
4 ft
.625 meter
1.25 meter
OtH (OTHER)

You can choose one of the four standard wheel sizes or select OTHER to choose the circumference of the measuring wheel.

The OTHER option allows you to input a wheel circumference ranging from ½ foot to 10 foot in circumference.

Refer to Section 2.0 operating procedures for a list of industry standard measuring heads and the settings to use with these heads.

Gr (GROOVE SIZE)

This setting allows you to choose the groove size of the measuring wheel (in inches). This setting can range from 0 (flat wheel) to a 1" groove.

The available sizes are:

.082
.092
.108

.125
3/16
7/32
1/4
OtH (OTHER)

If OTHER is selected you can enter any value from 0 (flat wheel) to a 1" groove.

SEt CL (SET CLOCK)

This feature provides a means to set the internal clock.

Use the following procedure to set the clock.

When SEf CL appears, press +

min (MINUTES) will then appear. Press the + or – switch until the correct minute (00-59) is selected then press MENU.

HOuR (HOUR) will next appear. Press the + or – switch until the correct hour is selected then press MENU. Note: The hours are set in 24 Hour format (01 – 24).

dAtE (DATE) will next appear. Press the + or – switch until the correct day of the month (1-31) is selected then press MENU.

mOnth (MONTH) will next appear. Press the + or – switch until the correct month (0-12) is selected then press MENU.

yEAR (YEAR) will next appear. Press the + or – switch until the correct year (0-99) is selected then press MENU.

StArt (START) will next appear. The time and date entered will now appear but the clock will not start until + is pressed. This feature can be used to synchronize the clock with an external clock.

4.4 OTHER (OtH)

This menu is to be used if you have a measuring device with a different wheel circumference than the standard Kerr measuring devices.

No line size selections are available

The available menu selections in the OTHER menu are:

Cr (WHEEL CIRCUMFERENCE)

This setting represents the circumference of the measuring wheel. Use the +/- switch to adjust the setting to match the circumference of the measuring wheel you are using.

AdJ (DEPTH ADJUST)

This setting is comparable to shimming a wheel. The amount selected will automatically be added or subtracted from the depth input. The values are feet / thousand.

Un (DEPTH UNITS)

This setting is used to set the display readout units to either FEET or METERS.

dir (DIRECTION)

This setting is used to reverse the counting direction. The depth should be increasing as you are going into the hole and decreasing as you are coming out of the hole. If it is going the opposite direction, use this setting to change it.


5.0 INSTALLATION AND MOUNTING

5.1 INSTALLATION PROCEDURE

- 5.1.1 Prepare an appropriate panel cut-out with four fixing holes.
- 5.1.2 Connect the magnetic pickup cable to the rear of the unit.
- 5.1.3 Ensure that power is off. Connect the unit to a 12vdc or 120/240 vac power supply.
- 5.1.4 Insert the display unit into the panel and secure it at the four corners.
- 5.1.5 Check that the magnetic pickup signal has the correct polarity. Move the measuring wheel in the direction of positive depth (down). If the display shows a negative value, it can be corrected by rotating the magnetic pickup on the measuring head by 180 degrees or changing the direction using from the menu.
- 5.1.6 Ensure that the unit is setup for the desired measurement units (feet or meters).
- 5.1.7 Before you start to use the display unit, leave it connected to the external power for 4 hours to ensure that the batteries are fully charged.

6.0 SPECIFICATIONS

6.1 DIMENSIONS



6.1 Mechanical

Material	Aluminium, anodized
Weight	1.5 lbs (.68 kg)
IP Rating	40
Temperature	0 to + 50 ° Centigrade
Humidity	10% - 80% RH non-condensing.

6.3 Electrical

Input power Voltage	100 - 240 VAC or 12 – 24 VDC
Input power frequency	50 - 60 Hz, DC

Input power current	0.4 A
---------------------	-------

6.4 Batteries

Battery	2100 mAh
Voltage	1.2 V NIMH
Lifetime	Approx. 5 years (depending on usage)

The batteries are trickle charged when external power is connected to the unit. The batteries are fully charged after 3 hours. The batteries discharge if the unit is left unpowered for a few weeks.

6.5 Power consumption and operating time

Operating	10 mA (typical)
Magnetic pickup assembly	20 mA (remainder powers the display)

6.6 AC Power Input

Live	Brown	White
Neutral	Blue	Black
Earth	Green/Yellow	Green

Power is fused inside the display unit case with a 250 mA fuse

6.7 DC Power-input

Live	Pin 1
Neutral	Pin 2
Earth	Pin 3

DC connector spec: AM5KP063 -CONN KPT06E8-33S 3 SOCKET

6.8 Depth measurement

Quadrature counts/revolution	16	
Measurement resolution	0.048 m	0.1573 ft
Display resolution	0.1 m	0.1 ft

6.9 Line Speed

Minimum Line Speed	0 ft/min
Maximum Line Speed	1200 ft/min

6.10 Power management

Power time-out with idle magnetic pickup	60 min
--	--------

The battery voltage and charge current can be displayed by pressing enable and menu at the same time.

The voltage will be displayed as:

E 4180

4180 would be a battery voltage of 4.18 volts. When the battery reaches 4.8v the charge will stop.

The charge current will be displayed as:

A 310

310 would be a battery charge current of 310 ma.

The display will cycle between the voltage and current display as long as the buttons are being depressed.

The charge current is limited to between 250 ma and 350 ma.

7.0 PARTS LISTS AND DIAGRAMS

7.1 PARTS LISTS

Item Number: ALS6A200 PANEL AMS BATT BKUP DISPLAY

Component	Description	Qty Required	UM
ALS6M021	PANEL FRONT 2X BKUP REAR MT	1	EA
ALS6M022	PANEL REAR 2X BKUP REAR MT	1	EA
AMS4P895	MEMORY CARD 512MB SD	1	EA
AMS5KP056	CONN KPT02E10-6S RECEPTACLE	1	EA
AMS4P257	CONN KPT02E8-33P RECEPTACLE	1	EA
AMS4P569	LCD 6 DIGIT .71" REFLECTIVE TN	0	EA
ALS6A020	PCB ASSY DEPTH SPEED DISPLAY	1	EA
AMS4P756	LIGHTPIPE 5/16 X 0.52 SEALED	1	EA
C276P155	CABLE BELDEN 177431 10' AC	1	EA
C276P151	RECEPTACLE 6ESRM-3 CORCOM AC	1	EA
AMS4P618	BATTERY 1.2V NIMH AA 2100MAH	3	EA
AMS4P021	SWITCH CAP ALCO C-22 BLACK	1	EA
AMS7P017	SWITCH CAP ALCO C-22 RED	1	EA
AMS4P631	NUT 1/4-40 DRESS BRIGHT NICKEL	4	EA
AMS4P659	CONN TERMINAL RECPTACLE .25TAB	3	EA
AMS7P021	CONN 102398-4 AMP 12 POS PCB	1	EA
AMS7P023	CONN 102536-4 AMP 12 POS BACK	1	EA
AMS7P024	CONN 102681-1 AMP 12 POS FRONT	1	EA
AMS4P661	CONN HOUSING 3POS 2.5MM SHROUD	1	EA
AMS4P662	CONN FE TERMINAL CRIMP 2.5MM	4	EA
AMS4P663	CONN HOUSING 2POS 2.5MM SHROUD	1	EA
ALS6P032	SCREW 4-40 X 3/8 FH PHIL SST	2	EA
ALS6P085	SCREW 4-40 X 1/4 FH PHIL SST	14	EA
AMS8P091	SCREW 4-40 X 1/4 PHIL PAN SST	12	EA
AMS8P036	WASHER #4 LOCK SST	13	EA
AMS4P626	WASHER #4 FLAT NYLON	1	EA
C276P158	NUT 4-40 MACHINE SST	1	EA
ALS6P026	SCREW 6-32 X 7/8 BTN HD SST	4	EA

USE ONLY 1.2V NIMH AA 2100MAH BATTERIES


WARNING

**DO NOT USE NON RECHARGEABLE
BATTERIES AS THEY ARE LIKELY TO
EXPLODE WHEN CHARGED**

7.2 Magnetic Pickup Cable – AM5KA024-XX

The wiring to the magnetic pickup is via a 6 pin MIL-C chassis socket. This is mounted with terminal A uppermost. The wiring to the magnetic pickup is pin-for-pin straight through.

Note: XX designates the cable length in feet



Function	Pin Number
Vsensor	A
Channel A	E
Channel B	C
Ground	D

Kerr P/N	Description	Qty	Required
AMS4P222	CABLE 20/4C ALPHA 25154 BLACK SHIELDED 0.28OD	XX	FT
AM5KP057	CONN KPT06F10-6P STR PLUG MS3116 W/STRAIN RELIEF	1	EA
AM5KP058	CONN KPT08F10-6S RT ANGLE PLUG W/STRAIN RELIEF OR EQUIVALENT	1	EA
AM5KP059	DUST CAP KPT8010C CANNON SHELL SIZE 10 OR EQUIV	2	EA
AM5KA034	BUSHING #9779-513-4 AMPHENOL	2	EA